

Dante™/AES67 POE+ Four Channel Class-D Network Audio Amplifier

PNA-D4 is the first product in Visionary's new PacketAV™ line of network AV endpoints. It is a (4/8 ohms) per channel network amplifier with Dante™/AES67 input that is powered via POE+, no external power supply required. It is a robust unit suitable for industrial, commercial and Pro AV installations. The unit is inherently a network device allowing it to deploy easily and enable precise control of your sound. Four independent channels can be sourced using any Dante™/AES67 audio on the network using Dante™ Controller software or other third party software. This unit is Class D to allow for efficient use of power.

Specifications

| | | | |
|-------------------------------|---|----------------------------|---|
| Audio Input: | Dante™/AES67 audio via Ethernet | Power Supply: | Power Over Ethernet + |
| Output Power: | 5W/channel 8 Ohms (20W Total) | Cooling Convection: | (No fan) |
| Minimum Total Load: | 2 Ohms | Controls: | Dante™ Controller Software |
| Frequency response: | (+0, -3dB, 1W) 20Hz – 20kHz THD+N < 0.1% @ 5W-8 Ohm load THD+N < 0.1% @ 5W-4 Ohm load | LED Indicators: | Power, Dante™, Status |
| Signal to Noise ratio: | > 99dB | Construction: | Steel Chassis |
| Standard Voltage Gain: | 25.2dB | Dimensions: | 109mm x 95mm x 29mm (W x D x H) Add 20mm W for mount flange |
| Power Consumption: | 2 Watts Standby, 25 Watts Maximum | Weight: | 0.4 kg |
| Input Connector: | RJ-45 | Warranty: | 2 Years Parts and Labor |
| Output Connector: | Euro Block | Plenum Rating: | UL2043 |

PNA-D4



 **Dante™/AES67**